




## Sirius AW10 15Kg Pet PIR Detector



### Connecting a Sirius AW10 15Kg Pet PIR Detector to a Sirius Alarm

#### Step 1 Connect to the Sirius Alarm

- 1 Turn on Power on the Detector
- 2 Select Walk Test on the Detector
- 3 Open your Smart Life or Tuya APP.
- 4 Open your Device
- 3 Tap Accessories.
- 4 Tap the + icon.
- 5 Now activate the Detector then tap Confirm.

#### Step 2 Setup the Zone Configuration

- 1 Tap on the Zone
- 2 Tap on Name and then Name your Detector then Save (for example Lounge PIR).
- 3 Tap Zone mode then scroll and choose what type of device mode you require Delay, Normal, 24Hr etc. Then Tap confirm.
- 4 Tap Type then scroll to the type of device you are connecting. In this case select Motion Detector, then Confirm.
- 5 Tap on Save then Confirm.

In accessories your Detector should display

Lounge, Type: Motion PIR, Mode: Normal

Make sure when you have finished to set the Detector to normal mode. See the Diagram above.

#### Deleting a Detector

- 1 Open the Smart Life or Tuya App.
- 2 Open your Device
- 3 Tap Accessories.
- 4 Select which Detector you want to Delete
- 5 Left scroll until the red rubbish bin is displayed now tap the icon.
- 6 Then Tap Confirm

#### To Change the Battery

Twist the head of the Detector from left to right when you are looking at the front of the detector. Remove the old Battery and install the new Battery